



**Note:** This API call is for DOS and Win16 personality only. Use [Family API](#) for portability.

2018/09/07 05:04 · prokushev · [0 Comments](#)

# Int 21H, AH=37H, AL=02H

## Version

2.x and 3.3+ only

## Brief

get availdev flag

## Family API

## Input

```
AH = 37h
AL = 02h get availdev flag
```

## Return

AL = status

```
00h successful
FFh unsupported subfunction
```

DL = 00h \DEV\ must precede character device names

```
= nonzero \DEV\ is optional
```

## Macro

## Notes

all versions of DOS from 2.00 allow \DEV\ to be prepended to device names without generating an error even if the directory \DEV does not actually exist (other paths generate an error if they do not exist); DOS 2.x has an AVAILDEV= option in CONFIG.SYS to make \DEV mandatory  
although MS-DOS 3.3+, DR DOS 3.41+, and Novell DOS 7 accept these calls, they have no effect, and AL=02h always returns DL=FFh (except for Novell DOS 7, which leaves AX unchanged for both subfunctions)

## See also

AX=3701h

## Note

Text based on [Ralf Brown Interrupt List Release 61](#)

<b>DOS API</b>	
Process manager	<a href="#">INT 20H</a> , <a href="#">INT 21H</a> : <a href="#">00H</a> , <a href="#">25H</a> , <a href="#">26H</a> , <a href="#">31H</a> , <a href="#">34H</a> , <a href="#">35H</a> , <a href="#">4BH</a> , <a href="#">4CH</a> , <a href="#">4DH</a> , <a href="#">50H</a> , <a href="#">51H</a> , <a href="#">52H</a> , <a href="#">55H</a> , <a href="#">62H</a> , <a href="#">INT 22H</a> , <a href="#">INT 27H</a> , <a href="#">INT 28H</a>
File manager	<a href="#">INT 25H</a> , <a href="#">INT 26H</a> , <a href="#">INT 21H</a> : <a href="#">0DH</a> , <a href="#">0EH</a> , <a href="#">0FH</a> , <a href="#">10H</a> , <a href="#">11H</a> , <a href="#">12H</a> , <a href="#">13H</a> , <a href="#">14H</a> , <a href="#">15H</a> , <a href="#">16H</a> , <a href="#">17H</a> , <a href="#">19H</a> , <a href="#">1AH</a> , <a href="#">1BH</a> , <a href="#">1CH</a> , <a href="#">21H</a> , <a href="#">22H</a> , <a href="#">23H</a> , <a href="#">24H</a> , <a href="#">27H</a> , <a href="#">28H</a> , <a href="#">29H</a> , <a href="#">2EH</a> , <a href="#">2FH</a> , <a href="#">32H</a> , <a href="#">3305H</a> , <a href="#">36H</a> , <a href="#">39H</a> , <a href="#">3AH</a> , <a href="#">3BH</a> , <a href="#">3CH</a> , <a href="#">3DH</a> , <a href="#">3EH</a> , <a href="#">3FH</a> , <a href="#">40H</a> , <a href="#">41H</a> , <a href="#">42H</a> , <a href="#">4300H</a> , <a href="#">4301H</a> , <a href="#">45H</a> , <a href="#">45H</a> , <a href="#">46H</a> , <a href="#">4EH</a> , <a href="#">4FH</a> , <a href="#">54H</a> , <a href="#">56H</a> , <a href="#">5700H</a> , <a href="#">5701H</a> , <a href="#">5AH</a> , <a href="#">5BH</a> , <a href="#">5c00H</a> , <a href="#">5c01H</a> , <a href="#">60H</a> , <a href="#">67H</a> , <a href="#">68H</a> , <a href="#">6900H</a> , <a href="#">6901H</a> , <a href="#">6AH</a> , <a href="#">6CH</a>
Character Device I/O	<a href="#">INT 29H</a> , <a href="#">INT 21H</a> : <a href="#">01H</a> , <a href="#">02H</a> , <a href="#">03H</a> , <a href="#">04H</a> , <a href="#">05H</a> , <a href="#">06H</a> , <a href="#">07H</a> , <a href="#">08H</a> , <a href="#">09H</a> , <a href="#">0AH</a> , <a href="#">0BH</a> , <a href="#">0AH</a> , <a href="#">0CH</a> , <a href="#">5D07H</a> , <a href="#">5D08H</a> , <a href="#">5D09H</a> , <a href="#">5D0AH</a>
Signals	<a href="#">INT 23H</a> , <a href="#">INT 24H</a> , <a href="#">INT 21H</a> : <a href="#">3300H</a> , <a href="#">3301H</a> , <a href="#">3302H</a>
Memory manager	<a href="#">INT 21H</a> : <a href="#">48H</a> , <a href="#">49H</a> , <a href="#">4AH</a> , <a href="#">5800H</a> , <a href="#">5801H</a> , <a href="#">5802H</a> , <a href="#">5803H</a>
Date and Time	<a href="#">INT 21H</a> : <a href="#">2AH</a> , <a href="#">2BH</a> , <a href="#">2CH</a> , <a href="#">2DH</a>
Misc	<a href="#">INT 21H</a> : <a href="#">30H</a> , <a href="#">3306H</a> , <a href="#">3700H</a> , <a href="#">3701H</a> , <a href="#">3702H</a> , <a href="#">3703H</a> , <a href="#">59H</a>
NLS	<a href="#">INT 21H</a> : <a href="#">3303H</a> , <a href="#">3304H</a> , <a href="#">3800H</a> , <a href="#">3801H</a> , <a href="#">6300H</a> , <a href="#">6301H</a> , <a href="#">6301H</a> , <a href="#">6500H</a> , <a href="#">6501H</a> , <a href="#">6502H</a> , <a href="#">6503H</a> , <a href="#">6504H</a> , <a href="#">6505H</a> , <a href="#">6506H</a> , <a href="#">6507H</a> , <a href="#">6520H</a> , <a href="#">6521H</a> , <a href="#">6522H</a> , <a href="#">6523H</a> , <a href="#">65A0H</a> , <a href="#">65A1H</a> , <a href="#">65A2H</a> , <a href="#">6601H</a> , <a href="#">6602H</a>
Devices	<a href="#">INT 21H</a> : <a href="#">4400H</a> , <a href="#">4401H</a> , <a href="#">4402H</a> , <a href="#">4403H</a> , <a href="#">4404H</a> , <a href="#">4405H</a> , <a href="#">4406H</a> , <a href="#">4407H</a> , <a href="#">4408H</a> , <a href="#">4409H</a> , <a href="#">440AH</a> , <a href="#">440BH</a> , <a href="#">440CH</a> , <a href="#">440DH</a> , <a href="#">440EH</a> , <a href="#">440FH</a> , <a href="#">4410H</a> , <a href="#">4411H</a> , <a href="#">53H</a>
Network	<a href="#">INT 21H</a> : <a href="#">5E00H</a> , <a href="#">5E01H</a> , <a href="#">5E02H</a> , <a href="#">5E03H</a> , <a href="#">5E04H</a> , <a href="#">5E05H</a> , <a href="#">5F00H</a> , <a href="#">5F01H</a> , <a href="#">5F02H</a> , <a href="#">5F03H</a> , <a href="#">5F04H</a> , <a href="#">5F05H</a> , <a href="#">5F07H</a> , <a href="#">5F08H</a>
<b>osFree Macro Library</b>	


<b>osFree Macro Library</b>	
Video I/O	@SetMode @SetCurSz @SetCurPos @GetCur @SetPage @ScrollUp @ScrollDn @Scroll @GetChAtr @PutChAtr @PutCh @SetPalet @SetColor @SetDot @GetDot @WrtTTY @VideoState @GetMode @GetDisplay @GetVideoState @GetEGAInfo @Cls
Hardware info	@Equipment @MemSize
Serial I/O	@AuxInit @AuxSendChar @AuxRecieveChar @AuxStatus
Tape I/O	@TapeOn @TapeOff @TapeRead @TapeWrite
Keyboard I/O	@KbdStatus @CharIn @CharPeek
Printer I/O	@PrnPrint @PrnInit @PrnStatus
Disk I/O	@DskReset @DskStatus @DskRead @DskWrite @DskVerify @DskFormat
Date and Time	@SetTime @GetTime
Mouse	@MouInit @MouShowPointer @MouStatus @MouSetPos @MouSetMickey @MouRegion
Memory manager	@ModBlok SET_BLOCK

2022/10/04 14:28 · prokushev · 0 Comments

2018/09/04 17:23 · prokushev · 0 Comments

<b>Family API</b>		
DOS	Process Manager	DosBeep DosExit DosSleep DosExecPgm
	File Manager	DosChDir DosChgFilePtr DosClose DosDelete DosDupHandle DosMkDir DosMove DosQCurDir DosQCurDisk DosSetFileMode DosOpen DosQFileInfo DosRead DosQFileMode DosQFSInfo DosQVerify DosRmdir DosSelectDisk DosFindClose DosFindFirst DosFindNext DosSetFileInfo DosSetVerify DosWrite DosFileLocks DosSetFHandState DosNewSize DosBufReset DosQFHandState DosSetFSinfo DosShutdown
	Memory Manager	DosFreeSeg DosSubAlloc DosSubFree DosSubSet DosAllocHuge DosAllocSeg DosReallocHuge DosReallocSeg DosGetHugeShift DosCreateCSAlias
	NLS	DosCaseMap DosGetCtryInfo DosGetDBCSEv DosSetCtryCode DosGetCollate DosGetMessage DosInsMessage DosPutMessage
	Date and Time	DosSetDateTime DosGetDateTime
	Devices	DosDevConfig DosDevIOct1 DosDevIOct2
	Signals	DosHoldSignal DosSetSigHandler
	Misc	BadDynLink DosGetEnv DosGetMachineMode DosGetVersion DosError DosErrClass DosSetVec
KBD		KbdCharIn KbdFlushBuffer KbdGetStatus KbdSetStatus KbdStringIn KbdPeek
VIO		VioGetBuf VioGetConfig VioGetCurPos VioGetCurType VioGetPhysBuf VioReadCellStr VioReadCharStr VioScrollUp VioScrollDn VioScrollLf VioScrollRt VioScrUnLock VioSetCurPos VioSetCurType VioSetMode VioGetMode VioShowBuf VioWrtCellStr VioWrtCharStr VioWrtCharStrAtt VioWrtNAttr VioWrtNCell VioWrtNChar VioWrtTTY VioScrLock VioPopUp
Tools		BIND
Modules		DOSCALLS.DLL VIOCALLS.DLL KBDCALLS.DLL MSG.DLL
Libraries		API.LIB OS2386.LIB FAPI.LIB DOSCALLS.LIB SUBCALLS.LIB

2018/08/25 15:05 · prokushev · 0 Comments



From:

<http://osfree.su/doku/> - **osFree wiki**

Permanent link:

<http://osfree.su/doku/doku.php?id=en:docs:dos:api:int21:37:02&rev=1607940212>

Last update: **2020/12/14 10:03**

